



LABOR INSTALLATION STANDARD

Dear NSCA Member:

These guidelines have been prepared to assist you in calculating your project labor estimates. According to our research, labor variables have become the single biggest risk factor in determining the true cost of each of your projects. This document helps you benchmark your labor productivity and efficiency against fellow NSCA members. We hope it helps you successfully and accurately prepare estimates and bids.

This data was compiled through months of peer reviews and discussions among integrators across North America. Preliminary results were analyzed, averaged, and rounded. Those results were then further analyzed to compare with the latest industry best practices, prevailing code requirements, and job-costing reports.

Please read the disclaimers and usage guidelines to better understand how these guidelines should be used. The labor units listed should be adjusted based on the conditions of each of your projects.

NSCA thanks the member companies and individuals that contributed to this report. Their assistance makes it a highly valuable resource for the entire industry.

Sincerely,



Chuck Wilson
Executive Director
NSCA



Kelly McCarthy
President
NSCA Board of Directors

TABLE OF CONTENTS

Page 4	2018 NSCA Labor Unit Survey
Page 5	Disclaimer
Page 6	Access Control
Page 7	Audio/Sound Reinforcement
Page 8	Cabling
Page 9	CATV/MATV
Page 10	CCTV
Page 11	Clocks
Page 11	Digital Signage
Page 12	Equipment Racks/Cabinets/Wall Plates
Page 13	Fiber Optics
Pages 14-15	Fire Alarm
Page 16	Industrial/Commercial Sound
Page 17	Networking
Page 18	Nurse Call
Page 19	Security & Alarm Systems
Page 20	Telephony
Pages 21-22	Video Presentation
Page 23	Videoconferencing & Unified Communications

WORK AND OPERATIONS COVERED BY LABOR UNITS

Material Handling

Prior to any equipment being installed, it must be handled several times. For example, the equipment must be unloaded from the delivery truck, cartons must be opened, and the equipment must be removed and tested. This requires material handling time before the equipment is installed, which must be accounted for. A nominal and typical amount of time at the jobsite *is included* in these basic labor units.

Drawings and Layouts

Prior to the equipment being installed, the installer/technician must become familiar with the equipment and work results at the installation site. It is imperative that time is spent examining shop drawings, scope documents, and other instructions. This project review time *is included* in basic labor units.

Note: This is only the jobsite portion for review time.

Equipment Installation

This portion includes the physical installation of electronic and related equipment in strict compliance with applicable codes, standards, and safety issues. This assumes that all miscellaneous parts, tools, and equipment are at the jobsite, and that installers are trained and operating at full utilization.

Supervision

Project management is an essential aspect of a successful job. For the purposes of this report, we have *not included* the time spent on general project management or design modifications. The cost of supervision by a crew foreman or lead technician *is included* in labor units for all job sizes.

LABOR UNITS

Labor units are based on favorable working conditions, production rates, and complete installation, including furnishing all equipment, connectors, anchors, cable ties, etc. When labor only is furnished, labor units may need to be adjusted upward to compensate for possible unknown conditions.

Degree-of-Difficulty Variables

Within the survey form, labor units under the *Normal* column are for heights up to 8 feet above a smooth, hard floor. Labor units under the *Difficult* column are for heights up to 12 feet. Labor units under the *Very Difficult* column are for heights up to 16 feet. Other examples are noted within.

Adjustment of Labor Units

Labor units may be adjusted for the following reasons:

- a – Installer/technician productivity, experience, and training
- b – Non-productive labor issues (beyond normal site conditions)
- c – Job factors (security clearance, safety training, job-specific provisions, etc.)

DISCLAIMER

IMPORTANT NOTICE: PLEASE READ CAREFULLY

THE FOLLOWING STANDARDS, WHICH WERE ESTABLISHED BASED ON A SURVEY OF NSCA MEMBERS, ARE DESIGNED AS A RESOURCE TO THE ELECTRONIC SYSTEMS INDUSTRY AND NSCA MEMBERS. PLEASE NOTE EACH OF THE FOLLOWING INSTRUCTIONS AND COMMENTS BEFORE UTILIZING THESE GUIDELINES:

1. THESE GUIDELINES SHOULD NOT BE VIEWED AS THE COMPLETE LABOR GUIDE FOR EVERYONE. THEY ARE ONLY PROVIDED AS A RESOURCE TO NSCA MEMBERS IF A MEMBER INDEPENDENTLY DETERMINES THAT IT DESIRES TO UTILIZE GUIDELINES OF THIS TYPE. ALL OR PART OF THE CONTENT OF THESE GUIDELINES MAY NOT FIT WITH OR BE APPLICABLE TO YOU OR YOUR COMPANY'S SITUATION.
2. NSCA PROVIDES NO REPRESENTATION OR WARRANTY (INCLUDING, BUT NOT LIMITED TO, IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE) OR ASSURANCE OF ANY TYPE REGARDING THIS STANDARD, ITS CONTENT, OR ITS SUITABILITY FOR USE BY YOU OR YOUR COMPANY. THE AVAILABILITY OF THIS STANDARD SHOULD NOT BE VIEWED AS A RECOMMENDATION BY NSCA THAT IT IS A PERFECT FIT FOR YOUR COMPANY'S SITUATION. ACTUAL JOB COSTING MAY BE NECESSARY FOR YOUR SITUATION IN LIEU OF OR IN ADDITION TO THE TYPE OF STANDARD INCLUDED.
3. THIS NOTICE AND THE INSTRUCTIONS CONTAINED HEREIN ARE IN ADDITION TO, AND NOT IN LIEU OF, THE "COPYRIGHT AND TRADEMARK NOTICE" AND THE "LEGAL NOTICE AND DISCLAIMER" FOUND AT THE BOTTOM OF THIS PAGE, AND SHALL NOT BE DEEMED TO LIMIT OR AMEND SUCH NOTICES AND DISCLAIMERS.

LEGAL NOTICE AND DISCLAIMER

THE TECHNICAL INFORMATION CONTAINED HEREIN IS PROVIDED TO THE NATIONAL SYSTEMS CONTRACTORS ASSOCIATION (NSCA) BY NSCA MEMBERS AND NON-MEMBERS. WHILE NSCA MAKES EVERY EFFORT TO PRESENT ACCURATE AND RELIABLE INFORMATION, NSCA DOES NOT CERTIFY, NOR CONFIRM, SITE CONDITIONS, NOR DOES IT GUARANTEE THE ACCURACY, COMPLETENESS, EFFICACY, TIMELINESS, OR CORRECT SEQUENCING OF SUCH INFORMATION. USE OF SUCH INFORMATION IS VOLUNTARY, AND RELIANCE ON IT SHOULD ONLY BE UNDERTAKEN AFTER TESTING IT AGAINST YOUR TYPICAL RESULTS FOR ACCURACY, COMPLETENESS, EFFICACY, AND TIMELINESS. REFERENCE HEREIN TO ANY SPECIFIC COMMERCIAL PRODUCT, PROCESS, OR SERVICE BY TRADE NAME, TRADEMARK, SERVICE MARK, MANUFACTURER, OR OTHERWISE DOES NOT CONSTITUTE OR IMPLY ENDORSEMENT, RECOMMENDATION, OR FAVORING BY NSCA.

NSCA (INCLUDING ITS EMPLOYEES AND AGENTS) ASSUMES NO RESPONSIBILITY FOR CONSEQUENCES RESULTING FROM THE USE OF INFORMATION HEREIN, OR IN ANY RESPECT FOR THE CONTENT OF SUCH INFORMATION, INCLUDING (BUT NOT LIMITED TO) ERRORS OR OMISSIONS, THE ACCURACY OR REASONABLENESS OF FACTUAL OR SCIENTIFIC ASSUMPTIONS, STUDIES OR CONCLUSIONS, THE DEFAMATORY NATURE OF STATEMENTS, OWNERSHIP OF COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHTS, AND THE VIOLATION OF PROPERTY, PRIVACY, OR PERSONAL RIGHTS OF OTHERS. NSCA IS NOT RESPONSIBLE FOR, AND EXPRESSLY DISCLAIMS ALL LIABILITY FOR, DAMAGES OF ANY KIND ARISING OUT OF USE, REFERENCE TO, OR RELIANCE ON SUCH INFORMATION. NO GUARANTEES OR WARRANTIES, INCLUDING (BUT NOT LIMITED TO) ANY EXPRESS OR IMPLIED WARRANTIES OR MERCHANTABILITY OR FITNESS FOR A PARTICULAR USE OR PURPOSE, ARE MADE BY NSCA WITH RESPECT TO SUCH INFORMATION.

ACCESS CONTROL

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS		
			PROGRAMMING	NORMAL	DIFFICULT
Controller	CPU/Computer		4.07	2.97	3.48
	Install Software	Proprietary	1.84	1.82	2.34
	Install Software	Mac or Windows Based	1.67	2.44	3.41
	Programming		5.06	N/A	N/A
	Computer Hookup/Setup	For Use with Access Prog.	N/A	2.68	3.89
	Build Card Database in Existing Software	Per 10 Cards*	2.17	1.99	2.32
	Artwork Layout	Photo Badging/Logo Cards	N/A	3.99	4.75
	Print Badging/Cards on Local Printer	Per 10 Cards	1.50	1.20	1.46
	Program Cards	Each	0.21	0.30	0.39
	Upload System Data to Remote Panels		1.50	1.10	1.26
Client Work Station		N/A**	3.00	3.83	
Access Control Panel	Control Panel	1 Reader	1.87	2.05	2.32
	Control Panel	2 Reader	2.31	3.47	4.14
	Control Panel	4 Reader	3.13	5.34	6.44
	Control Panel	8 Reader	4.83	7.89	9.39
	Control Panel	8 to 16 Reader	7.19	11.84	14.83
	Card Reader	Standalone	2.22	2.52	3.98
	Power Supply (12VDC)		N/A	1.26	1.54
	Power Supply (24VDC)		N/A	1.26	1.54
	Battery Back-Up		N/A	0.70	1.04
	Elevator Interface-Relay Based	Driven by Controller Panel	1.00	2.86	3.60
Input Control Board		1.00	1.98	3.46	
Output Control Board		1.00	1.97	3.15	
Door Access Devices	Card Reader (prox, swipe, or touchpad)	Wall Mounted	0.54	1.20	1.50
	Card Reader (prox, swipe, or touchpad)	Post Mounted	0.54	1.66	2.08
	Reader/Door Controller		2.69	2.01	2.43
	Palm/Fingerprint/Iris Biometric Reader		1.13	1.86	2.33
	Door Contacts		0.25	1.05	1.31
	Request-to-Exit Motion Detector		0.83	1.30	1.60
	Telephone Door Entry Security		2.17	2.38	3.00
	Remote Intercom Unit		N/A	1.48	1.90
Door Lock Devices	Door Strike	Electric - New	0.25	2.28	2.64
	Door Strike	Electric - Retrofit	0.25	2.43	3.08
	Mortice Lock	Electric - New	0.25	2.70	2.92
	Mortice Lock	Electric - Retrofit	0.25	2.61	3.22
	Electric Hinge		0.25	1.95	2.39
	Door Lock	Touchpad - New	0.25	2.32	2.82
	Door Lock	Touchpad - Retrofit	N/A	2.52	3.17
	Mag-Lock (Single Door)		0.50	3.02	4.48
	Mag-Lock (Double Door)		0.50	4.98	7.47
	Mag-Lock	Emergency Door, 15-Sec. Delay	0.25	5.02	7.51
	RIM Lock		N/A	2.03	3.02
	Push-Bar Exit Device		0.25	3.07	4.49
Push-Bar Exit Device	Electrified w/ Power Supply	0.25	5.97	8.96	
Miscellaneous	Door Lock Protector		N/A	0.94	1.48
	Key Switch		N/A	0.93	1.55
	Door Closer		N/A	1.95	2.36
	NEMA Enclosure		N/A	1.20	1.65
	Relay/sockets		N/A	0.84	1.08
	Motion Sensor		N/A	1.00	1.32
	Bell/Horn		N/A	1.01	1.28
	Emergency Door Release	Push Button	N/A	1.00	1.12
Surge Protector		N/A	0.51	N/A	

* Programming is for database set up; labor is for entering data.

** Programming included in labor hours.

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Examples: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Note: Labor hours include handling and unpacking of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

For wiring, see Cabling on page 8.

AUDIO/SOUND REINFORCEMENT

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	COMMISSIONING & PROGRAMMING	LABOR HOURS		
				NORMAL	DIFFICULT	CHALLENGING
Digital Signal Processing	Digital Signal Processor (DSP)		3.93	2.63	5.02	N/A
	Digital Signal Processor (DSP) with AEC DSP I/O Interface		6.00	2.63	5.02	N/A
	DSP Computer/Software		4.09	2.87	4.03	N/A
	DSP Computer/Software		4.32	3.69	6.01	N/A
Mixing Console	Mixing Console (1-8 inputs) - Analog	Rack/Desk Mounted	1.62	2.60	3.12	N/A
	Mixing Console (8-16 inputs) - Analog	Rack/Desk Mounted	2.18	4.09	4.97	N/A
	Mixing Console (8-16 inputs) - Digital	Rack/Desk Mounted	2.25	4.16	4.93	N/A
	Mixing Console (17-32 inputs) - Analog	Desk Mounted	3.30	5.91	6.73	N/A
	Mixing Console (17-32 inputs) - Digital	Desk Mounted	3.32	5.79	6.67	N/A
	Mixing Console (32+ inputs) - Analog	Desk Mounted	4.84	7.17	8.75	N/A
	Mixing Console (32+ inputs) - Digital	Desk Mounted	4.90	7.25	8.73	N/A
	E-Control Add-On	WiFi Router, Connections, Programming, etc.	3.00	N/A	N/A	N/A
Audio Components	Equalizer	Digital	1.59	1.70	2.04	N/A
	Equalizer	Analog	1.35	1.62	1.86	N/A
	Compressor/Limiter	Digital	1.16	1.38	1.92	N/A
	Compressor/Limiter	Analog	1.13	1.37	1.75	N/A
	Ambient Sensing		2.28	1.80	2.75	N/A
	Automatic Mic Mixer (1-8 inputs)		2.01	1.88	2.10	N/A
	Power Amplifier		1.03	1.31	1.75	N/A
	Power Amplifier with built-in DSP		1.50	1.31	1.75	N/A
	Wired Microphone		N/A	0.21	1.15	N/A
	Microphone Outlet		N/A	0.95	1.69	N/A
	Microphone Table Top		N/A	0.28	0.97	N/A
	Ceiling Microphone		N/A	0.50	1.00	N/A
	Wireless Microphone		0.13	0.21	1.02	N/A
	Remote Antennas	Wireless Mic	N/A	0.47	3.33	N/A
	Digital Snake		0.23	0.49	3.50	N/A
	Beamforming Ceiling Microphone - 3 elements		1.00	0.75	1.00	
Beamforming Ceiling Microphone - 8 elements		4.00	1.00	1.50		
Speakers				STEP LADDER	EXT. LADDER	LIFT
	Wall Speaker	Surface Mount	N/A	1.42	1.63	1.88
	Wall Speaker	Flush Mount	N/A	1.60	1.82	2.10
	Ceiling Speaker	Surface Mount	N/A	1.48	1.70	1.81
	Ceiling Speaker	Flush Mount	N/A	1.38	1.58	1.88
	Monitor Speaker		N/A	1.28	1.44	1.63
Speaker Clusters, Array, 2-3 Box	WITHOUT BUILT-IN ATTACHMENT					
	Box Speaker	<40#	N/A	4.10	4.80	5.80
	Box Speaker	>40#	N/A	4.35	5.13	5.86
	L F Speaker/1 H F Horn		N/A	4.05	4.80	5.65
	L F Speaker/2 H F Horn		N/A	4.65	5.28	6.70
	L F Speaker/3 H F Horn		N/A	4.78	5.80	7.98
Speaker Clusters, Array, 2-3 Box	WITH BUILT-IN ATTACHMENT					
	Box Speaker	<40#	N/A	3.01	3.50	4.35
	Box Speaker	>40#	N/A	3.41	3.98	5.10
	L F Speaker/1 H F Horn		N/A	3.67	4.50	5.42
	L F Speaker/2 H F Horn		N/A	4.54	5.37	6.60
	L F Speaker/3 H F Horn		N/A	4.88	5.85	7.26

Programming involves creating user presets and default settings, as well as saving and storing the files. Commissioning includes the final installation, set up, and training.

Normal - Basic install and design that can be done from a step ladder.

Difficult - Examples: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures, requirement of an extension ladder.

Challenging - Examples: Padded ceiling with multiple obstructions, requirement of a lift.

Labor hours include handling and unpacking of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

For wiring, see Cabling on page 8.

CABLING

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS		
			NORMAL	DIFFICULT	CHALLENGING
Cable Installation	Single Cable 1- to 8-pair	per 100'	1.13	1.60	2.38
	Single Cable 8- to 24-pair	per 100'	1.16	1.96	2.51
	Single Cable 25-pair	per 100'	1.36	2.21	2.87
	Single Cable 50-pair	per 100'	1.82	2.54	3.09
	Single Cable 100-pair+	per 100'	2.09	3.18	4.05
	Two-to-Four Cables 1- to 8-pair	per 100'	1.67	2.42	3.13
	Five + Cables 1- to 8-pair	per 100'	2.24	2.85	3.93
	Single Cable Coax	per 100'	1.04	1.53	2.19
	Two to Four Cables Coax	per 100'	1.49	1.99	2.66
	Five + Cables Coax	per 100'	1.91	2.58	3.18
Pre-Terminated Cable Installation	HDMI/DVI/VGA	per 50'	0.52	1.49	2.21
	Component/S-Video/Composite	per 50'	0.50	1.46	2.27
Termination	Category Cable Termination	Remote End	0.40	0.51	0.98
	Category Cable Termination	Head End	0.52	0.50	1.00
	25 Pair (per end)		1.63	2.03	2.36
	Coax	"F" Style	0.27	0.29	0.62
	Coax	BNC	0.35	0.33	0.68
	Audio Cable	XLR	0.38	0.42	0.72
	Audio Cable	RCA	0.33	0.36	0.68
	Audio Cable	Mini	0.25	0.29	0.52
	Install Punch Block (66)	25-Pair	1.08	1.31	1.72
	Install Patch Panel (RJ45)	24-Port	1.63	1.30	1.60
Testing	Cat 5		0.55	0.17	0.25
	Cat 6/6A		0.60	0.17	0.25
	25-pair		1.11	0.25	0.25
	Coax	OTDR	0.60	0.25	0.26

* Difficult and Challenging assume obstructions and a difficult bend radius.

Normal - Example: Suspended ceiling.

Difficult - Examples: No conduit/raceway provided, above normal ceiling height.

Challenging - Examples: No conduit/raceway provided, lift required, limited access ceiling.

Note: Labor hours include handling and unpackaging of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

Cable installation hours do not include the removal of abandoned cable.

For healthcare facilities specifying CDC guidelines for dust containment and infectious control, add 35% to the Challenging column figure.

CATV/MATV

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS		
			NORMAL	DIFFICULT	CHALLENGING
Accessories	TV Receptacle		0.56	0.89	1.50
	Splitter/Directional Coupler		0.52	0.67	0.84
	Head End Equipment (passive devices)		3.29	4.35	6.23
	QAM Modulator		0.94	1.89	2.92
	QAM Demodulator		0.97	1.92	2.97
	Broadband Amplifier		0.94	1.83	2.78
	Satellite Receiver		0.93	1.91	2.99
	Multiplexer		1.02	1.99	3.01
Antenna/Satellite Dish			POLE MOUNT	ROOF MOUNT	INCLEMENT WEATHER
	Antenna (off-air)		3.41	4.09	5.59
	Satellite Dish	18" (DSS - LNB Included)	1.98	2.82	4.71
	Satellite Dish	4' (LNB Included)	3.75	4.83	6.26
	Satellite Dish	6' (LNB Included)	4.48	5.60	7.10
	Satellite Dish	8' (LNB Included)	5.61	6.52	8.33

For displays, see Video Presentation on page 21.

Normal - Example: Connecting to a single monitor.

Difficult - Example: Distributing to multiple rooms/devices.

Challenging - Examples: Integrating multiple video sources; remodulating and distributing.

Note: Labor hours include handling and unpackaging of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

For wiring, see Cabling on page 8.

CCTV

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS			
			NORMAL	DIFFICULT	CHALLENGING	
Controller	CPU/Computer		0.55	0.96	3.50	
	Software Load		0.48	1.57	3.00	
	Programming		2.12	4.05	6.00	
	Computer Hookup/Setup	For Use with CCTV Prog.	0.47	0.79	4.00	
	Install Software	DOS/Windows Based	0.52	1.88	4.00	
	Camera Programming	Each Camera	0.10	0.14	1.50	
	Viewing Station (passive - no control)		1.05	1.31	2.00	
Mounting	Power Bracket		1.02	1.44	1.86	
	Camera Control Unit		1.66	2.18	2.78	
	Mount	Standard	0.84	1.24	1.85	
	Mount	Swivel	0.97	1.35	2.61	
	Mount	Tamper-Proof	1.16	1.58	2.13	
	Mount	Automatic Pan	1.60	2.07	2.86	
	Mount	Corner	1.41	1.91	2.47	
	Mount	Parapet	2.10	3.12	3.92	
	Mount	Pole Mount - 20 Ft Max	3.74	4.95	5.79	
Camera and Support Bracket			STEP LADDER	EXT. LADDER	LIFT	
	Indoor Camera	Fixed	1.22	1.58	2.11	
	Indoor Camera	Pan/Tilt	2.01	2.50	3.08	
	Indoor Camera and Housing	Fixed	1.72	2.16	2.65	
	Indoor Camera and Housing	Pan/Tilt	2.33	3.00	3.73	
	Outdoor Camera with Housing	Fixed	2.37	2.93	3.45	
	Outdoor Camera and Housing	Pan/Tilt	3.01	5.47	4.56	
	Indoor Dome Camera	Fixed	1.75	2.34	2.94	
	Indoor Dome Camera	Pan/Tilt	2.25	2.91	3.58	
	Outdoor Dome Camera	Fixed	2.58	3.51	4.39	
	Outdoor Dome Camera	Pan/Tilt	3.57	4.37	5.42	
	Heater		0.59	0.85	1.15	
	Blower		0.63	0.83	1.16	
	Sun-Shroud		0.62	0.98	1.22	
	Wiper		0.76	1.05	1.32	
	IP Camera	Set IP Address	0.35	0.49	N/A	
	Indoor Mini Dome Camera		1.21	1.75	2.09	
	Outdoor Mini Dome Camera		2.13	2.93	3.38	
	Monitor	Monitor Bracket	Wall	1.34	1.98	2.62
		Monitor Bracket	Ceiling	1.78	2.41	3.66
Monitor in Rack		Install	1.02	1.45	1.97	
Monitor in Rack		Fabricate	1.98	2.92	3.67	
Accessories	Digital Video Recorder - DVR	Desktop	1.06	1.59	2.05	
	Digital Video Recorder - DVR	Rack Mount	1.46	2.06	2.62	
	Network Video Recorder - NVR		1.37	2.20	2.81	
	Server Build Up		1.24	2.06	N/A	
	Storage Area Network - SAN		1.89	2.46	N/A	
	Distribution Amplifier		1.18	1.46	1.88	
	Remote Control Box (Pan/Tilt/Zoom/Focus)	Desktop	1.57	2.02	2.45	
	Remote Control Box (Pan/Tilt/Zoom/Focus)	Rack Mount	1.76	2.12	2.59	
	Remote Power Supply		1.07	1.61	1.93	
	Switcher	Desktop	1.56	1.93	2.49	
	Switcher and Mounting Bracket	Rack Mount	1.96	2.49	3.01	
	Coax Surge Suppressor		0.64	0.89	1.08	
	Console		2.90	3.86	4.90	
	Pan/Tilt/Zoom Lens Control		1.61	2.53	2.97	
	Time/Date/Character Generator		1.37	1.79	2.20	
	Digital Motion Detector		1.35	1.95	2.44	
	Video Processor	4 Inputs	1.75	2.12	2.60	
	Alarm Interface		1.77	2.17	2.70	
	Programming	Per Channel	0.68	1.34	1.62	
IP Encoder		0.53	2.00	4.00		
Camera Lenses	Fixed		0.53	0.65	0.99	
	Auto Iris		0.65	0.90	1.37	
	Zoom		0.87	1.03	1.26	
	Add or Replace Lens		0.75	1.22	1.81	

Normal - Examples: Install camera from step ladder, easy access to work location.

Difficult - Examples: Install camera from lift or extension ladder, difficult access to work spaces.

Challenging - Examples: Install camera with high lift outdoors in obscure area (e.g. edge of roof) and/or incompatible equipment, high-security venues, or challenging weather conditions.

Note: Labor hours include handling and unpacking of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

For wiring, see Cabling on page 8.

CLOCKS

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS	
			NORMAL	DIFFICULT
Master Clock	Single Circuit Controller & Programming	Flush	3.58	4.87
	Single Circuit Controller & Programming	Surface	3.15	4.43
	Multi Circuit Controller & Programming	Flush	5.03	6.65
	Multi Circuit Controller & Programming	Surface	5.04	6.79
	Wireless Master		5.80	8.08
Secondary Clock	Secondary Clock	Digital	0.80	1.36
	Secondary Clock	Analog	0.85	1.24
	Secondary Clock	with Wire Guard	0.71	1.23
	Secondary Clock and Speaker	with Wire Guard	0.90	1.43
	Secondary Clock and/or speaker	Digital	1.60	1.95
	Backbox		1.59	2.01
	Secondary Clock and/or speaker	Analog	1.04	1.38
	Backbox		0.99	1.20
	Elapsed Time Clock		0.50	0.99
	Elapsed Time Control		0.49	1.07

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Example: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Note: Labor hours include handling and unpackaging of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

DIGITAL SIGNAGE

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS	
			NORMAL	DIFFICULT
Content Server	Install & Configuration	Furnished by Others (IT)	6.07	7.37
	Content Design Services and Programming	Basic	7.98	9.62
	RSS Feed Capability	Connectivity Only	1.10	1.65
	Streaming Video	Connectivity Only	1.01	1.74
	Database Integration	Furnished by Others (IT)	4.88	6.53
	Wayfinding	Implementation per location	3.10*	4.17*
	User Training	Remote Training for Basic and Advanced Settings	4.00	6.00
Player Install	Wired Configuration		1.52	2.03
	Wireless Configuration		1.40	2.30
	Owner Network Configuration	Furnished by Others (IT)	1.88	2.71
	Antivirus Installation	Furnished by Others (IT)	1.56	1.88
	Update Media Player Software		1.51	2.56
	Add Coaxial TV Input		1.38	2.19
	Multiple Display Output		2.66	3.20
	Display Scheduling and Control		0.75	1.50
Display Install	Interactive Display		0.75	1.50
	Mobile/Fixed Kiosk ≤ 46"		3.75	6.35
	Mobile/Fixed Kiosk > 46"		4.12	6.87
	Custom Kiosk/Display ≤ 46"		5.86	7.89
Custom Kiosk/Display > 46"		6.23	8.01	

* Graphics/design furnished by others.

For displays, see Video Presentation on page 21.

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Example: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Note: Labor hours include handling and unpackaging of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

EQUIPMENT RACKS/CABINETS/WALL PLATES

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS	
			NORMAL	DIFFICULT
Equipment Racks & Cabinets	Field Installation	Floor Mount 42"-77"	2.90	3.67
	Staging/Pre-Assembly/Cable Dress	Floor Mount 42"-77"	3.00	3.00
	Blank Panels	Each	0.34	0.67
	Ventilation Panel /Fan	Each	0.58	0.84
	Power Strip	Each	0.71	0.97
	AC Power Panel/Sequencer		0.90	1.18
	Wall Equipment Cabinet	28" or Less	2.05	3.08
	Wall Equipment Cabinet	Over 28"	2.82	3.97
Wall Plates & Floor Boxes	Audio	≤ 2 connections per gang	0.62	1.41
	Audio	> 2 connections per gang	1.20	1.45
	Network	≤ 2 connections per gang	0.98	1.32
	Network	> 2 connections per gang	1.40	1.68
	Video	≤ 2 connections per gang	0.60	1.25
	Video	> 2 connections per gang	0.90	1.41

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Example: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Note: Labor hours include handling and unpackaging of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

Note: Preassembly has been added, assuming that this will be done prior to rack being shipped to jobsite.

FIBER OPTICS

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS		
			NORMAL	DIFFICULT	CHALLENGING
Fiber Optic Cable Pulling	2- to 6-Strand in Conduit	per 100'	1.24	1.93	3.16
	2- to 6-Strand in Cable Tray	per 100'	1.27	2.09	3.53
	2- to 6-Strand in Inner-Duct	per 100'	1.04	1.71	3.05
	12- to 36-Strand in Conduit	per 100'	1.59	2.60	3.87
	12- to 36-Strand in Cable Tray	per 100'	1.60	2.70	4.13
	12- to 36-Strand in Inner-Duct	per 100'	1.38	2.39	3.62
	12- to 36-Strand Self Supporting (rings)	per 100'	2.40	3.62	5.10
	48+-Strand in Conduit	per 100'	1.83	2.97	4.33
	48+-Strand in Cable Tray	per 100'	1.84	3.06	4.59
	48+-Strand in Inner-Duct	per 100'	1.70	2.64	4.04
Inner-Duct Placement			STEP LADDER	EXT. LADDER	LIFT
	Inner-Duct	per 100'	2.66	3.18	3.93
Termination Multimode	Breakout Kit 6-Strand	Per End	1.20	2.90	3.52
	Breakout Kit 12-Strand	Per End	1.93	3.89	4.91
	ST Termination	Per Connector	0.40	0.92	1.62
	SC Termination	Per Connector	0.39	0.88	1.59
	FC Termination	Per Connector	0.61	0.92	1.59
	SMA Termination	Per Connector	0.74	1.07	1.52
	Fusion Splicing	Per Strand	0.74	1.28	1.81
Termination Singlemode	Breakout Kit 6-Strand	Per End	1.34	3.10	3.77
	Breakout Kit 12-Strand	Per End	1.96	3.24	4.41
	Breakout Kit 24-Strand	Per End	2.96	3.63	5.66
	ST Termination	Per Connector	0.43	0.92	1.84
	SC Termination	Per Connector	0.42	0.92	1.84
	FC Termination	Per Connector	0.63	0.92	1.84
	SMA Termination	Per Connector	0.78	1.07	1.84
	Fusion Splicing	Per Strand	0.73	1.28	1.81
Hardware	Wall-Mount LIU (Lightguide Interface Unit)	6- to 12-port	1.25	2.45	3.52
	Wall-Mount LIU (Lightguide Interface Unit)	12- to 24-port	1.52	2.95	4.02
	Wall-Mount LIU (Lightguide Interface Unit)	36+-port	2.00	3.85	4.75
	Rack-Mount LIU (Lightguide Interface Unit)	6- to 12-port	1.22	2.35	3.39
	Rack-Mount LIU (Lightguide Interface Unit)	12- to 24-port	1.57	3.15	4.14
	Rack-Mount LIU (Lightguide Interface Unit)	36+-port	2.07	4.15	4.92
	Rack-Mount Splice Center		1.17	2.92	3.85
	Splice Capsule	3-Tray	1.61	3.19	4.13
	Splice Capsule	6-Tray	1.68	3.19	4.25
Testing			TESTING AVERAGE	DOCUMENTATION AVG.	
	Singlemode One Direction Per Strand	OTDR	0.44	0.63	N/A
	Multimode One Direction Per Strand	OTDR	0.44	0.63	N/A
	Singlemode One Direction Per Strand	Power Meter	0.50	0.51	N/A
	Multimode One Direction Per Strand	Power Meter	0.50	0.51	N/A
	Singlemode Splice Loss	OTDR	0.54	0.63	N/A
Multimode Splice Loss	OTDR	0.69	0.97	N/A	

Normal - Example: Suspended ceiling.

Difficult - Examples: No conduit/raceway provided, above normal ceiling height.

Challenging - Examples: No conduit/raceway provided, lift required, limited access ceiling.

Note: Labor hours include handling and unpacking of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

FIRE ALARM

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS			
			PROGRAMMING	NORMAL	DIFFICULT	CHALLENGING
Controllers	4 Zone		1.54	2.61	3.21	4.01
	8 Zone		1.85	3.53	4.22	5.39
	12 Zone		2.84	4.66	5.41	6.64
	24 Zone		4.38	6.28	7.16	8.95
	48 Zone		7.33	9.38	10.67	12.80
	Addressable Controller		3.74	5.29	6.22	8.07
	Battery, with Rack		N/A	1.43	1.91	2.61
	Battery Charger		N/A	1.37	1.61	2.14
	Relay		1.39	0.91	1.10	1.45
	Test Switch		1.00	0.92	1.10	1.44
	Remote Annunciator		1.45	0.98	1.16	1.47
	Fireman's Phone		1.25	1.21	1.48	1.94
	Digital Communicator		1.61	1.81	2.27	2.87
	Remote Interface		2.20	1.67	1.90	2.46
Function Circuit Card		1.11	1.30	1.69	2.28	
Annunciators	8 Zone		1.00	1.90	2.95	3.88
	12 Zone		1.37	2.10	3.12	4.87
	16 Zone		1.74	2.26	3.00	4.21
	24 Zone		2.14	2.67	3.44	4.39
	48 Zone		3.32	3.24	4.35	5.35
	Addressable Annunciators		1.98	2.13	2.50	3.11
Detection Devices				STEP LADDER	EXT. LADDER	LIFT
	Heat Detector	Hours Conventional	0.25	0.99	1.10	1.43
	Heat Detector	Hours Addressable	0.47	0.93	1.15	1.39
	Smoke Detector	Hours Conventional	N/A	1.03	1.23	1.53
	Smoke Detector	Hours Addressable	0.47	0.97	1.21	1.51
	Duct Smoke Detector	Hours Conventional	N/A	1.91	2.20	2.53
	Duct Smoke Detector	Hours Addressable	0.50	1.95	2.19	2.77
	Manual Pull Station	Hours Conventional	N/A	1.01	1.36	1.64
	Manual Pull Station	Hours Addressable	0.47	0.97	1.36	1.66
	Explosion-Proof Pull Station		N/A	1.59	1.88	2.35
	Remote Test Station		N/A	0.93	1.22	1.58
	Remote LED Detector		N/A	0.92	1.12	1.46
	Signaling Devices	Horn		N/A	1.01	1.20
Weatherproof Horn			N/A	1.27	1.45	1.65
Amplified Horn			N/A	1.08	1.35	1.88
Horn/Strobe			N/A	1.21	1.47	1.82
Bell			N/A	1.03	1.23	1.53
Weatherproof Bell			N/A	1.20	1.38	1.68
Audio/Visual			N/A	1.03	1.24	1.54
Strobe Light			N/A	1.05	1.24	1.55
Explosion Proof Strobe Light			N/A	1.66	1.86	2.05
Rotating Beacon			N/A	1.48	1.82	2.10
Speaker 8 Inch		Ceiling	N/A	1.07	1.50	1.91
Speaker 4 Inch		Wall	N/A	0.99	1.36	1.63
Speaker/Strobe		N/A	1.15	1.36	1.66	
Miscellaneous	Magnetic Door Release		N/A	1.26	1.68	2.09

FIRE ALARM, CONTINUED

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS			
			PROGRAMMING	NORMAL	DIFFICULT	CHALLENGING
PC Configuration	Printers		N/A	1.58	1.94	2.46
	Keyboard and Monitor		N/A	1.61	1.90	2.40
	Graphics PC		N/A	0.32	N/A	N/A
	Software		2.00	1.00	2.00	4.00
Control Panel Modules	Control Relay Module		N/A	0.94	1.14	1.37
	4 Circuit Signal Module		N/A	1.10	1.31	1.78
	Panel-Mount Control Switch		N/A	0.92	1.25	1.72
	Power Supply - 6 Amps		N/A	1.17	1.58	2.10
	Voice Telephone Command		N/A	1.99	2.53	3.15
	Master Firefighter's Telephone		N/A	1.64	2.01	2.79
	30 to 80 Watt Amplifier		N/A	1.46	1.80	2.25
	80 to 250 Watt Amplifier		N/A	1.87	2.25	2.70
	Audio Message Generator		N/A	1.92	2.04	2.38
Fire Alarm Devices	Guard for Stations		N/A	0.72	0.92	1.25
	Pressure Switch - No Plumbing		N/A	1.11	1.36	1.65
	Firefighter's Phone		N/A	1.09	1.32	1.63
	Firefighter's Phone Jack		N/A	0.94	1.11	1.41
	4PSDT Relay/Surface-Mount Enclosure		N/A	0.95	1.19	1.48
	Magnetic Door Release		N/A	1.19	1.41	1.77
	Flow Switch - No Plumbing		N/A	1.20	1.43	1.76
	Tamper Switch		N/A	1.14	1.35	1.67
	Adapter Plate		N/A	0.52	0.73	0.95
	Trim Plate		N/A	0.50	0.70	0.95
	Addressable Device (Remote)		0.75	0.97	1.15	1.40
	Keyboard and Monitor		N/A	1.90	2.20	2.62

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Examples: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Challenging - Examples: Padded ceiling with multiple obstructions, requires a lift.

Note: Labor hours include handling and unpackaging of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

INDUSTRIAL/COMMERCIAL SOUND

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS		
			NORMAL	DIFFICULT	CHALLENGING
Intercom - Master Stations	Master Assembly	Desktop	2.61	3.50	4.14
	Master Assembly	Rack	3.17	3.98	4.69
	Termination	Per Room	0.69	1.13	1.51
Remote Stations	Call Switch	Existing Box	0.68	0.96	1.37
	Call Switch	Drywall Ring Only	1.24	1.54	2.25
Amplifiers/Mixers	Package Amp/Mixer	Shelf Mounted	1.53	1.85	2.50
	Package Amp/Mixer	Rack Mounted	1.50	1.82	2.35
	Modular Package Amp/Mixer	Shelf Mounted	1.86	2.20	2.89
	Modular Package Amp/Mixer	Rack Mounted	1.86	2.10	2.64
	Module - Insert & Connect		0.65	0.99	1.29
	Power Amplifier	Rack Mounted	1.15	1.40	1.75
	Wall Amplifier		2.27	3.17	4.23
Program Sources	Tuner, Tape, Radio, CD Player etc.		0.96	1.29	1.94
	Telephone Line Paging		0.95	1.54	2.19
Signal Processors	Equalizer	Install/Connect	1.32	1.93	2.68
	Equalizer	Setup Equalization	1.92	2.28	2.96
	Compressor/Limiter	Install/Setup	1.19	1.59	2.14
	Ambient Sensing	Auto Level Set	1.82	2.25	3.08
	Zone Switching	Manual	1.29	2.02	3.06
	Zone Switching	Relay	1.62	2.41	3.59
	Microphone		0.72	1.14	1.53
	Microphone Outlet		0.86	1.23	1.68
Digital Page Delay		1.19	1.61	2.15	

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Examples: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Challenging - Examples: Padded ceiling with multiple obstructions, lift required.

Note: Labor hours include handling and unpacking of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

NETWORKING

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS					
			ETHERNET	GIGABIT	INTEGRATOR PROVIDED	IT DEPT. FURNISHED		
Hubs	Non-Stackable		0.39	0.46	N/A	N/A		
	Non-Stackable w/ Built-In Management		0.47	0.49	N/A	N/A		
	Non Stackable w/ Add-In Management Module		0.65	0.55	N/A	N/A		
	Stackable		0.48	0.49	N/A	N/A		
	Stackable w/ Built-In Management		0.57	0.52	N/A	N/A		
	Stackable w/ Add-In Management Module		0.75	0.58	N/A	N/A		
	Up Link Modules		0.37	0.42	N/A	N/A		
Switches	Non-Stackable		1.00	1.55	N/A	N/A		
	Non-Stackable w/ Built-In Management		1.22	1.80	N/A	N/A		
	Non Stackable w/ Add-In Management Module		1.48	1.89	N/A	N/A		
	Stackable		1.23	1.90	N/A	N/A		
	Stackable w/ Built-In Management		1.32	1.80	N/A	N/A		
	Stackable w/ Add-In Management Module		1.58	2.45	N/A	N/A		
	Up Link Modules		0.49	0.45	N/A	N/A		
	Enterprise Chassis		1.82	1.83	N/A	N/A		
	Switch Fabric		2.20	2.10	N/A	N/A		
	Interface Module		0.39	0.65	N/A	N/A		
	Layer 3 Switching/Routing		3.15	3.20	6.00	3.00		
	Trunking, STP, Redundant Links		2.88	2.65	4.00	2.00		
	VLAN Implementation		2.55	2.40	8.00	4.00		
			LABOR HOURS					
			CHASSIS	FRAME	ETHERNET	GIGABIT	INTEGRATOR PROVIDED	IT DEPT. FURNISHED
Routers	Boundary Router		1.12	1.00	2.79	3.33	N/A	N/A
	Assignment of IP Addresses						1.00	0.50
	Mid-Tier Router		1.00	1.10	3.30	3.50	N/A	N/A
	Layer 3 Switching/Routing		0.88	0.92	3.80	4.44	6.00	3.00
	VLAN Implementation/Routing/Subnet		0.74	0.95	3.75	4.04	8.00	4.00
	Enterprise Router		1.50	0.86	6.05	5.87	N/A	N/A
	Interface Card		0.75	1.05	1.20	1.20	N/A	N/A
	Layer 3 Switching/Routing		0.88	1.00	3.79	4.00	6.00	3.00
	VLAN Implementation/Routing/Subnet		1.10	0.89	6.00	6.05	8.00	4.00
Network Management			SOFTWARE				INTEGRATOR PROVIDED	IT DEPT. FURNISHED
	Operating System (Built-In)		2.50				2.00	N/A
	Windows Based		4.35				2.00	N/A
	Proprietary Operating System		3.87				2.00	N/A
	Client-Developed Solution						TBD	TBD
Wireless Networks					ETHERNET		INTEGRATOR PROVIDED	IT DEPT. FURNISHED
	Access Points/SSID Config				1.10		2.00	0.50
	Wireless Controller				1.50		1.00	0.50

Normal - Basic install with no unforeseen obstructions or procedures. Network devices will be placed in a controlled environment with easy access.

Note: Labor hours include handling and unpackaging of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

NURSE CALL

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS		
			NORMAL	DIFFICULT	CHALLENGING
Audiovisual (Non-Microprocessor)	Master Station		3.85	5.26	6.46
	Central Equipment & Power Supply		6.41	7.77	9.98
	Patient Station	Single or Dual	1.36	1.69	2.23
	Patient Station with Entertainment		1.49	2.25	2.75
	Lavatory/Pull Station		1.05	1.26	1.81
	Call Cord/Pillow Speaker		0.54	1.02	1.41
	Staff Station		1.23	1.54	1.96
	Duty Station		1.24	1.54	1.96
	Dome Light		1.10	1.38	1.92
	Zone Light		1.08	1.42	1.92
	Corridor Light		1.10	1.39	1.96
	Annunciator Panel	Remote	3.64	4.13	5.19
	Psychiatric Station		1.46	1.74	2.51
	Explosion-Proof Station		1.56	1.96	2.55
Explosion-Proof Switch		1.44	1.81	2.48	
Power Supply		1.60	1.83	2.53	
Tone Visual Only (Non-Microprocessor)	Master Annunciator	25 Room w/Backbox	5.62	6.45	7.74
	Master Annunciator	50 Room w/Backbox	6.23	8.44	9.92
	Master Annunciator	100 Room w/Backbox	13.01	15.06	18.07
	Power Supply	with Backbox	2.23	2.62	3.39
	Patient Station	Single or Dual	1.22	1.49	1.86
	Lavatory/Bath Station		1.04	1.27	1.74
	Dome Light		1.00	1.28	1.77
Audiovisual (Microprocessor)	Power Supply	with Backbox	2.08	2.97	3.43
	CPU/Central		6.51	7.75	9.19
	Monitor and Keyboard		2.32	2.82	3.49
	Printer		1.39	1.97	2.80
	Patient Station	Single or Dual	1.26	1.54	1.67
	Bed Station Call Cord		0.85	1.03	1.32
	Lavatory/Bath Station		0.93	1.26	1.51
	Staff Station		1.25	1.57	1.89
	Duty Station		1.30	1.69	2.03
	Dome Light		1.03	1.28	1.50
Zone Light		1.07	1.25	1.40	
Pocket Paging/Computer Interface/Telephony		5.23	6.50	7.78	
Code Blue System	Central Equipment		6.39	7.35	7.69
	Nurses' Station		3.76	5.82	7.02
	Annunciator Panel		5.65	6.70	8.09
	Call Station		1.10	1.82	2.58
	Corridor Light		0.87	1.34	1.88
	Zone Light		0.93	1.34	2.06
Power Supply		1.56	1.80	2.31	
VoIP Nurse Call	Nurse Call Server		8.15	N/A	N/A
	Gateway		2.65	N/A	N/A
	Switch		1.98	N/A	N/A
	VoIP Patient Station		1.20	1.44	1.73
	Graphical Workflow Station		3.89	4.67	5.60
	Report Server		6.67	N/A	N/A
	Messaging Server		4.15	N/A	N/A
	Real-Time Localization Server (RTLS)		5.02	N/A	N/A
ADT Integration		6.33	N/A	N/A	

Normal - New construction with conduit and cabling support system already installed.

Difficult - New construction without conduit and cabling support system already installed or existing construction with conduit and cabling support system.

Challenging - Existing construction without conduit and cabling support system already installed.

Note: Labor hours include handling and unpacking of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

For healthcare facilities specifying CDC guidelines for dust containment and infectious control, add 35% to the Challenging column figure.

SECURITY & ALARM SYSTEMS

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS			
			PROGRAMMING	NORMAL	DIFFICULT	CHALLENGING
Alarm Systems	Infrared Motion Detector		N/A	0.87	1.12	1.64
	Ultrasonic Motion Detector		N/A	0.80	1.12	1.68
	Magnetic Door Switch	Surface	N/A	0.82	1.18	1.48
	Magnetic Door Switch	Flush	N/A	0.97	1.38	1.78
	Foil Tape	Per Foot	N/A	0.82	1.21	1.44
	Tape Switch		N/A	0.84	1.25	1.78
	Panic Button	Surface	N/A	1.03	1.18	1.41
	Panic Button	Flush	N/A	0.79	1.14	1.62
	Key Switch		N/A	0.76	1.09	1.57
	Photo Electric Detector		N/A	0.91	1.09	1.48
	Digital Key Pad		N/A	0.91	1.24	1.68
	Electric Door Strike		N/A	1.41	1.69	2.14
	Horn		N/A	0.77	1.11	1.59
	Bell		N/A	0.75	1.10	1.59
	Electronic Speaker/Siren		N/A	0.82	1.06	1.64
	Glass Break Detector		N/A	0.77	1.08	1.38
Glass Break Detector	Wireless	N/A	0.68	0.94	1.26	
Keypad	Wireless	N/A	0.75	1.04	1.58	
Alarm Signal Devices	Bell		N/A	0.79	1.18	1.64
	Indoor Horn/Siren		N/A	0.83	1.15	1.62
	Indoor Strobe		N/A	0.82	1.10	1.36
	Outdoor Horn/Siren		N/A	1.05	1.44	1.84
	Backbox	Flush	N/A	0.68	1.02	1.35
	Backbox	Surface	N/A	0.67	0.96	1.30
	Control Panel		1.03	2.80	3.45	4.47
	Expansion Module		1.10	1.40	1.72	2.08
	Digital Communicator		0.89	1.54	1.90	2.41
	Panel Programming per Zone		0.66	0.86	1.26	1.74
Annunciators	Basic Units/Modules	Installation	0.75	1.11	1.43	1.88
	Installation	Per Zone Module	N/A	0.77	1.18	1.69
	Backbox		N/A	0.67	0.99	1.38
Control Panel	Small	Residential/Commercial	1.80	2.20	2.62	3.14
	Medium	Commercial	3.05	2.31	2.96	3.46
	Large	Commercial	5.20	3.33	3.98	4.78
	Separate Annunciator Panel		1.67	1.61	1.98	2.45
	Remote Control Unit		1.38	1.38	1.84	2.44
	Wireless Console	Residential	1.00	1.02	1.49	1.97
	Wireless Panel	Residential	1.10	1.65	2.13	2.51
	Wireless Panel	Commercial	2.50	2.27	2.63	3.23
	Zone Expansion Module		1.07	1.32	1.73	2.17
	Logic Module		1.23	0.96	1.34	1.82
	AC Failure Module		0.75	0.83	1.18	1.68
Installation	Per Zone Module	N/A	0.82	1.24	1.75	
Backbox		N/A	0.75	1.10	1.50	
Peripherals	Separate Digital Comm.		1.35	1.25	1.99	2.50
	Cellular Phone Link		1.25	1.77	2.38	2.80
	Telephone Control Module		1.05	1.14	1.61	2.08
	Receiver	Single Channel	1.67	1.27	1.64	2.27
	Receiver	2 Channel	1.78	1.30	1.69	2.33
	Receiver	4 Channel	2.88	1.91	2.28	2.93
Receiver	8 Channel	5.05	2.56	3.14	3.95	
Power Supply	Battery		N/A	0.64	1.38	2.19
	Battery Rack		N/A	0.74	1.28	1.95
	Charger		N/A	0.86	1.21	1.82
	Indicator Panel		1.00	1.05	1.59	2.25
	Switch Over Control		1.10	1.05	1.41	2.15

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Examples: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Challenging - Examples: Padded ceiling with multiple obstructions, lift required.

Note: Labor hours include handling and unpackaging of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

TELEPHONY

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS					
			END-USER TRAINING	END-USER DATA COLLECTION	IN-SHOP PROGRAMMING	ON-SITE PROGRAMMING	NORMAL	DIFFICULT
KSU	Small (<12 Port)	With Standalone Voice Mail	3.25	2.42	2.53	3.91	3.65	4.60
	Small (<12 Port)	With Integrated Voice Mail	2.85	2.42	2.20	3.00	2.40	4.12
	Small (<12 Port)	Without Voice Mail	2.56	2.10	1.97	2.08	1.95	3.30
	Medium (>12 Port)	With Standalone Voice Mail	4.80	3.81	3.75	4.92	3.75	5.20
	Medium (>12 Port)	With Integrated Voice Mail	3.40	3.71	3.43	4.00	3.67	4.50
	Medium (>12 Port)	Without Voice Mail	3.40	3.14	3.20	2.92	3.25	3.90
PBX	Medium (12-128 Port)	With Standalone Voice Mail	8.20	5.21	6.93	2.05	1.74	3.60
	Medium (12-128 Port)	With Integrated Voice Mail	8.00	5.08	6.10	1.71	1.75	2.97
	Medium (12-128 Port)	Without Voice Mail	5.80	4.89	4.07	1.50	1.50	3.15
	Large (>128 Port)	With Standalone Voice Mail	12.40	8.80	8.75	2.15	2.23	3.45
	Large (>128 Port)	With Integrated Voice Mail	10.80	8.60	7.50	1.95	2.05	3.10
	Large (>128 Port)	Without Voice Mail	8.40	8.20	5.50	1.97	1.87	3.03
Hybrid	Small (<64 Port)	With Standalone Voice Mail	11.10	3.05	6.46	6.06	3.21	5.10
	Small (<64 Port)	With Integrated Voice Mail	10.65	3.81	5.57	5.94	2.95	5.13
	Small (<64 Port)	Without Voice Mail	7.40	3.54	3.19	4.75	2.11	3.90
	Medium (64-128 Port)	With Standalone Voice Mail	12.10	5.91	7.91	8.44	3.41	6.30
	Medium (64-128 Port)	With Integrated Voice Mail	10.95	5.88	7.21	8.25	3.35	6.17
	Medium (64-128 Port)	Without Voice Mail	9.00	5.42	4.19	6.75	2.10	5.70
	Large (>128 Port)	With Standalone Voice Mail	12.75	8.43	10.83	14.49	7.55	10.75
	Large (>128 Port)	With Integrated Voice Mail	13.07	8.07	10.00	13.71	7.26	9.67
	Large (>128 Port)	Without Voice Mail	11.00	7.36	7.17	10.71	6.12	9.33
	Install Plywood 4 X 4		N/A	N/A	N/A	N/A	2.10	3.50
	Install Enclosure		N/A	N/A	N/A	N/A	2.67	4.25
	Install & Connect Power Supply		N/A	N/A	N/A	N/A	1.20	4.31
	Install Battery Back-Up Unit	Internal	N/A	N/A	N/A	N/A	1.15	2.20
	Install Battery Back-Up Unit	External	N/A	N/A	N/A	N/A	1.25	2.29
	Install Admin Phone	Digital - Per Phone	N/A	N/A	N/A	N/A	0.89	1.17
	Install Wall/Desk Phone	Digital - Per Phone	N/A	N/A	N/A	N/A	0.85	1.15
	Install Admin Phone	Analog - Per Phone	N/A	N/A	N/A	N/A	1.05	1.30
	Install Wall/Desk Phone	Analog - Per Phone	N/A	N/A	N/A	N/A	1.45	1.82
	Install Busy Lamp Field	<64	N/A	N/A	N/A	N/A	1.19	1.55
	Install Busy Lamp Field	64-128	N/A	N/A	N/A	N/A	1.48	1.56
	Install Busy Lamp Field	>128	N/A	N/A	N/A	N/A	1.52	1.71
	Punch Down/Label Block	<64	N/A	N/A	N/A	N/A	3.80	5.85
	Punch Down/Label Block	64-128	N/A	N/A	N/A	N/A	4.56	8.10
	Punch Down/Label Block	>128	N/A	N/A	N/A	N/A	7.85	9.75
VoIP Systems	Communication Server/Gateway		N/A	4.10	2.40	N/A	2.15	3.10
	Voice Mail Server		N/A	2.60	2.40	N/A	2.03	2.75
	Voice Switch		N/A	1.40	2.10	N/A	1.87	3.21
	IP Phone		0.25	0.15	N/A	0.51	0.88	1.60
	PC Software		2.00	2.40	N/A	3.10	1.15	N/A
	PC Soft Phone		0.25	0.15	N/A	0.67	0.65	1.48
	PC Operator Software		3.00	N/A	N/A	2.15	1.52	N/A

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Examples: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Note: Labor hours include handling and unpacking of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

For wiring, see Cabling on page 8.

VIDEO PRESENTATION

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS		
			PROGRAMMING	NORMAL	DIFFICULT
Projectors with Mounts	Projector - < 5000 lumen	Surface Mount - Ceiling	0.39	2.88	6.13
	Projector - < 5000 lumen	Suspended Ceiling	0.42	2.94	5.85
	Projector - < 5000 lumen	Rear Screen	0.52	3.63	5.97
	Projector - < 5000 lumen	Table or Cabinet - No Mount	0.52	1.04	3.08
	Projector - motorized** < 5000 lumen	Ceiling	0.49	4.75	8.26
	Projector - motorized** < 5000 lumen	Table or Cabinet	0.44	3.88	5.50
Projectors with Heavy-Duty Mounts	Projector - > 5000 lumen	Surface Mount - Ceiling	0.55	3.33	5.50
	Projector - > 5000 lumen	Suspended Ceiling	0.47	3.71	6.23
	Projector - > 5000 lumen	Rear Screen	0.47	4.11	4.91
	Projector - > 5000 lumen	Table or Cabinet - No Mount	0.49	1.07	2.10
	Projector - motorized** > 5000 lumen	Ceiling	0.51	7.67	9.59
	Projector - motorized** > 5000 lumen	Table or Cabinet	0.53	5.33	8.16
Screens	Screen ≤ 100" - manual	Wall Mount	N/A	1.63	3.06
	Screen ≤ 100" - manual	Ceiling Mount	N/A	1.75	2.89
	Screen ≤ 100" - manual	Ceiling Mount - Recessed	N/A	3.00	4.80
	Screen ≤ 100" - motorized**	Recessed Ceiling	N/A	4.75	7.00
	Screen ≤ 100" - motorized**	Wall Mount	N/A	3.00	5.50
	Screen ≤ 100" - motorized**	Ceiling Mount	N/A	3.25	6.15
	Screen > 100" - manual	Wall Mount	N/A	2.44	5.00
	Screen > 100" - manual	Ceiling Mount	N/A	2.63	4.96
	Screen > 100" - manual	Ceiling Mount - Recessed	N/A	4.95	8.15
	Screen > 100" - motorized**	Recessed Ceiling	N/A	6.75	9.85
Screen > 100" - motorized**	Wall Mount	N/A	4.50	7.12	
Screen > 100" - motorized**	Ceiling Mount	N/A	5.06	8.00	
Displays	Display < 46"	Wall Mount - Stationary/Tilt	0.44	2.00	2.85
	Display < 46"	Wall Mount - Extending	0.45	2.50	3.12
	Display < 46"	Pole Mount	0.44	2.38	3.87
	Display < 46"	Ceiling Mount < 10'	0.50	2.25	3.40
	Display < 46"	Ceiling Mount ≥ 10'	0.46	3.38	4.33
	Display < 46"	Freestanding	0.51	1.63	2.48
	Display < 46"	Motorized* - Table/Cabinet	0.51	3.13	4.67
	Display < 46"	Motorized* - Ceiling Mount	0.50	3.75	5.39
	Display > 46" - 2 installers***	Wall Mount - Stationary/Tilt	0.47	2.33	3.15
	Display > 46" - 2 installers***	Wall Mount - Extending	0.48	3.17	3.95
	Display > 46" - 2 installers***	Pole Mount	0.52	2.50	4.05
	Display > 46" - 2 installers***	Ceiling Mount < 10'	0.50	2.67	3.65
	Display > 46" - 2 installers***	Ceiling Mount ≥ 10'	0.44	3.33	4.87
	Display > 46" - 2 installers***	Freestanding	0.56	1.83	2.25
	Display > 46" - 2 installers***	Motorized* - Table/Cabinet	0.51	3.50	5.37
	Display > 46" - 2 installers***	Motorized* - Ceiling Mount	0.52	4.50	5.85
	Furniture Mounted	Huddle Space Kit	N/A	2.00	3.00

VIDEO PRESENTATION, CONTINUED

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS		
			PROGRAMMING*	NORMAL	DIFFICULT
Interactive Whiteboard	Interactive Whiteboard	Freestanding	1.65	2.25	3.50
	Interactive Whiteboard	Wall Mount	1.49	2.97	4.50
	Document Camera		0.88	1.75	3.35
	Interactive Podium/Instructor Device		1.43	3.00	4.45
Miscellaneous	Audience Response Systems	≤ 15 units	2.40	1.75	N/A
	Audience Response Systems	16 to 30 units	3.80	1.75	N/A
	Audience Response Systems	> 30 units	5.00	1.82	N/A
Direct View LED Wall	Below 70 sq ft - 2 installers***	Wall Mount	4.00	13.00	19.00
	70 sq ft and above - 3 installers**	Wall Mount	4.00	17.00	24.00
	Commissioning/Testing		8.00	N/A	N/A

* Programming on projectors and displays includes set up of basic functions and default settings.

** Motorized includes wiring for basic wall switch and remote control.

*** Labor hours need to be multiplied by number of installers.

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Examples: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Note: Labor hours include handling and unpackaging of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

VIDEOCONFERENCING & UNIFIED COMMUNICATIONS

	INSTALLATION ITEMS	ADDITIONAL DESCRIPTION	LABOR HOURS		
			PROGRAMMING*	NORMAL	DIFFICULT
Videoconferencing/Unified Communications	Camera/Webcam	Wall Mount	1.50	2.33	3.86
	Camera/Webcam	Ceiling Mount	1.45	2.54	4.12
	Camera/Webcam	In-Wall Mount	1.48	3.33	4.79
	Desktop Video Conference		1.50	1.67	2.15
	Camera Control Console		2.50	4.00	7.25
	Remote Control System for Camera Control		2.50	2.50	3.85
	Image Controller		1.50	1.00	1.88
	Call Server/Codec		1.50	1.98	2.30
	Multipoint Conferencing Unit		2.50	3.15	4.00
	Gateway Device		N/A	2.00	4.00
	Echo Cancellation Mixer		N/A	2.00	3.95
	Microphone Mixer/Switcher		1.55	2.67	5.20
	Tabletop Speakerphone/Conference phone		1.00	1.83	3.66
	Wireless Microphone System	4 or less	1.03	2.17	4.35
Wireless Microphone System	5 or more	1.50	3.17	6.05	
Video Switching/Processing/Control					
	16-32 Inputs		2.25	2.40	4.60
	Less than 8 Inputs		0.75	1.00	3.00
	8-16 Inputs		1.50	1.50	3.50
	32-64 Inputs		3.00	4.00	7.00
	Greater than 64 Inputs		4.50	8.00	12.00
	Network Video Endpoint		0.50	1.00	2.33
Video Extender Set		0.25	1.00	1.50	
AV Control Section	Control Processor		6.00	1.50	2.50
	Control Touch Panels - 10" and Under		8.00	0.75	1.50
	Control Touch Panels - Above 10"		12.00	1.00	2.00
	Occupancy Sensor		1.00	0.75	1.00
	Divide Combine Logic Programming		16.00	N/A	N/A
	Lighting Control Programming		6.00	N/A	N/A
	Shade Control Programming		4.00	N/A	N/A
	HVAC Control Programming - BACnet		8.00	N/A	N/A
Room Scheduling Panels		1.00	1.00	1.50	

* Programming on projectors and displays includes setup of basic functions and default settings.

Normal - Basic install with no unforeseen obstructions or procedures.

Difficult - Examples: Installation in heights exceeding 10 feet, overcoming unforeseen obstructions and/or extensive programming, facilities that require heightened security procedures.

Note: Labor hours include handling and unpacking of equipment, testing, and time spent confirming drawings, diagrams, plans, etc.

